

SOLITON WAVE GENERATOR ELECTRICAL NEUTRON BOMB

NOTE : THIS DEVICE IS IN CURRENT TOP SECRET USE BY THE MILITARY, IT HAS BEEN FOR OVER 15 YEARS. THIS DESIGN IS EXTREMELY SIMILAR TO THE MILITARY'S DESIGN. CAREFUL.


THINK OF IT AS A COMPRESSED BUNDLE OF ELECTROMAGNETIC WAVES THAT ARE ISOLATED AND DOES NOT DISPERSE ITS ENERGY OVER LARGER AND LARGER REGIONS OF SPACE. A SOLITON HAS EXTREMELY DESTRUCTIVE POTENTIAL. THE SOLITON THAT THIS DEVICE WILL CREATE IS CAPABLE OF WIPING OUT A POWER PLANT OR POWER STATION. IT IS SUCH A SIMPLE DESIGN, THIS KNOWLEDGE MUST NOT GET INTO THE WRONG HANDS. THE SOLITON WAVE EMITTED FROM THIS DEVICE WILL ACT LIKE A NEUTRON BOMB'S WAVE, WHICH WILL DESTROY ALL ELECTRONIC DEVICES WITHIN IT'S REACH. THE DEVICE WILL CREATE A KIND OF BUBBLE OF ENERGY THAT DOES THE WORK. UNFORTUNATELY THE DEVICE AND MOST THINGS AROUND IT WILL ALSO BE DESTROYED, FROM THE EXPLOSION.

THE THEORY IS COMPLICATED, BUT EXPLAINABLE.

THE MAIN CIRCUIT IS NOTHING MORE THAN A BANK OF CAPACITORS AND A SILVER RING. THE CAPACITIVE CHARGE IS INTRODUCED INTO THE SILVER RING WHICH IS IMMERSSED IN A FLUX MATERIAL. THE CHARGE IS INTRODUCED WITH A HIGHLY EFFICIENT, HIGH POWER RELAY SWITCH. THE RELAY WILL CONTACT THE CHARGE AND THE CURRENT TO THE DETONATORS. THE EXPLOSIVE CHARGE IS DESIGNED AROUND THE OUTSIDE OF THE FLUX, ABOUT AN INCH. ONCE THE CHARGE IS FED INTO THE RING, THE RELAY WILL ALSO INITIATE THE DETONATORS, THEREBY THE EXPLOSIVES (C4 OR TNT). THE DETONATION AND CHARGE RELEASE MUST OCCUR WITHIN 1/1000SEC OF EACH OTHER IN ORDER FOR THE SOLITON TO BE CREATED. ONCE THE RING IS ENERGIZED IT WILL ALMOST IMMEDIATELY DISINTEGRATE, BEFORE IT DISINTEGRATES IT WILL EMIT AN EXTREMELY POWERFUL MAGNETIC FIELD, THIS FIELD STARTS TO GROW JUST AS THE EXPLOSION IMPLODES IT. REMEMBER THAT WHEN AN EXPLOSION OCCURS IT CREATES A MAGNETIC FIELD OR EM PULSE, POWERFUL. ONCE THE TWO FIELDS COLLIDE THEY FORM THE SOLITON WAVE. THIS WAVE EMITS IN ALMOST ALL DIRECTIONS FROM THE DEVICE. A DEVICE THE SIZE OF A SHOEBOX WILL TAKE OUT A POWER PLANT. ONE THE SIZE OF A CAR COULD TAKE OUT A SMALL CITY.

THE PARTS TO BUILD THIS DEVICE ARE EASY TO GET...THE HARDEST PART IS THE EXPLOSIVES, SO WE INCLUDED A "HOW TO MAKE C4, ETC" BOOKLET. WE HOPE SOMEONE CAN FIGURE OUT HOW TO MAKE IT ALL ELECTRICAL INSTEAD OF DESTRUCTION OF THE ENTIRE DEVICE. CAPS AND CHARGING CIRCUITS AREN'T CHEAP!!!

HERE IS THE PICTORAL DIAGRAM:



WE ARE NOT LIABLE FOR ANY DAMAGE, DEATH, HARM OR PROPERTY DAMAGE, ETC. CAUSED BY ANY DEVICE, PART, KIT, OR PLANS/SCHEMATICS OBTAINED FROM UUE.

HOW TO MAKE C4, IMPROVISED

HERE ARE TWO TYPES OF EXPLOSIVES THAT WILL WORK WITH THIS DEVICE:

1. KINTRITE
2. PLASTIQUE

KINTRITE

MATERIALS=AMMONIUM NITRATE FERTILIZER, NITROMETHANE, #8 DETONATOR.

(2.25 CUPS) HEAT UP THE AN=AMMONIUM NITRATE UNTIL IT BOILS AND TURNS BROWN. REMOVE THE AN AND LET IT HARDEN.... CRUSH IT INTO A POWDER AND PLACE IN A DRY AIR TIGHT CONTAINER.

(1 CUP) HEAT UP THE NITROMETHANE UNTIL IT BOILS, LET BOIL FOR 15 SECONDS. POUR THE NITROMETHANE ON THE AN WHEN IT IS STILL HOT.

PLACE MIXTURE IN WHATEVER CONFIGURATION YOU NEED AND PLACE A CONTAINMENT CAGE OR STEEL STRUCTURE AROUND IT, PLACE DETONATOR WHEN IT COOLS DOWN.

PLASTIQUE

MATERIALS=BULLS EYE SMOKELESS GUN POWDER, NITROMETHANE, ALUMINUM POWDER, POTASSIUM CHLORATE.

BOIL THE NITROMETHANE FOR 15 SECONDS.

MIX 1 CUP NITROMETHANE WITH ½ CUP POTASSIUM CHLORATE WITH 5 TEASPOONS OF ALUMINUM POWDER WITH 2 CUPS OF SMOKELESS POWDER.

WE ARE NOT LIABLE FOR ANY USE OR MISUSE OF THIS OR ANY OTHER INFORMATION OBTAINED FROM UUE OR ANY OTHER SOURCE. IT IS THE RESPONSIBILITY OF THE READER OR USER OF THIS OR ANY OTHER DOCUMENT TO OBSERVE SAFETY PRECAUTIONS.